onsemi

DATA SHEET www.onsemi.com

NPN General-Purpose Amplifier

MPSA05

Features

- This Device is Designed for General–Purpose Amplifier Applications at Collector Currents to 300 mA
- These Devices are Pb-Free, Halogen Free/BFR Free and are RoHS Compliant

MAXIMUM RATINGS

Symbol	Symbol Parameter		Unit	
V _{CEO}	Collector-Emitter Voltage	60	V	
V _{CBO}	V _{CBO} Collector-Base Voltage		V	
V _{EBO}	Emitter-Base Voltage	4.0	V	
Ι _C	I _C Collector Current – Continuous		mA	
T_J , T_{STG}	T _J , T _{STG} Junction and Storage Temperature		°C	

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

THERMAL CHARACTERISTICS

Values are at $T_A = 25^{\circ}C$ unless otherwise noted.

Symbol	Parameter	Max.	Unit
PD	Total Device Dissipation	625	mW
	Derate Above 25°C	5.0	mW/°C
$R_{\theta JC}$	Thermal Resistance, Junction-to-Case	83.3	°C/W
R_{\thetaJA}	Thermal Resistance, Junction-to-Ambient	200	°C/W




Emitter Base

Collector

TO-92-3 CASE 135AR Bent Lead Tape & Reel

1

MARKING DIAGRAM



ORDERING INFORMATION

Device	Package	Shipping [†]
MPSA05RA	TO-92 3L	2000 / Tape & Reel

[†]For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, <u>BRD8011/D</u>.

ELECTRICAL CHARACTERISTICS

Values are at $T_A = 25^{\circ}C$ unless otherwise noted.


Symbol	Parameter	Conditions	Min.	Max.	Unit
V _{(BR)CEO}	Collector-Emitter Breakdown Voltage (Note 1)	I _C = 1 mA, I _B = 0	60	-	V
V _{(BR)EBO}	Emitter-Base Breakdown Voltage	$I_{\rm E} = 100 \ \mu {\rm A}, \ I_{\rm C} = 0$	4	-	V
I _{CEO}	Collector Cut-Off Current	$V_{CE} = 60 \text{ V}, \text{ I}_{B} = 0$	-	0.1	μA
I _{CBO}	Collector Cut-Off Current	$V_{CB} = 60 \text{ V}, \text{ I}_{E} = 0$	-	0.1	μA
h _{FE}	DC Current Gain	I _C = 10 mA, V _{CE} = 1.0 V	100	-	
		I_{C} = 100 mA, V_{CE} = 1.0 V	100	-	
V _{CE} (sat)	Collector-Emitter Saturation Voltage	I _C = 100 mA, I _B = 10 mA	-	0.25	V
V _{BE} (on)	Base-Emitter On Voltage	I _C = 100 mA, V _{CE} = 1.0 V	-	1.2	V
f _T	Current Gain – Bandwidth Product	I_{C} = 10 mA, V_{CE} = 2 V, f = 100 MHz	100	-	MHz


1. Pulse Test: Pulse Width \leq 300 $\mu s,$ Duty Cycle \leq 2%.



TO-92 3 4.83x4.76 LEADFORMED CASE 135AR ISSUE O

DATE 30 SEP 2016





NOTES: UNLESS OTHERWISE SPECIFIED

A) DRAWING WITH REFERENCE TO JEDEC TO-92 RECOMMENDATIONS.

- B) ALL DIMENSIONS ARE IN MILLIMETERS.
- C) DRAWING CONFORMS TO ASME Y14.5M-1994

DOCUMENT NUMBER:	BAON13879G Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.		
DESCRIPTION:	TO-92 3 4.83X4.76 LEADFORMED		PAGE 1 OF 1

onsemi and ONSEMi are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

onsemi, ONSEMI, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or indental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification. Buyer shall indemnify and hold onsemi and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs,

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

Technical Library: www.onsemi.com/design/resources/technical-documentation onsemi Website: www.onsemi.com

ONLINE SUPPORT: <u>www.onsemi.com/support</u> For additional information, please contact your local Sales Representative at <u>www.onsemi.com/support/sales</u>